

j5create

USB 3.0 Multi-Adapter Gigabit Ethernet & 3-Port HUB (JUH470)

Mac & Windows Compatible

User Manual



INTRODUCTION

The j5 create USB 3.0 Multi-Adapter series provides extra connectivity from your computer with 5Gb/S faster transfer speed. These pocket-sized Multi- adapters allow you to add an additional USB computer peripherals and Gigabit LAN through you USB port.

With Gigabit Combo adapter allows you to add networking capabilities to a computer without them through a Wi-Fi connection. It has a RJ-45 connector that supports 10/100/1000 Mbps Ethernet performance, it is perfect for your Ultrabook or MacBook.

This series with alternative solution are simply Fast, Portable and elegant for whatever you might need.

SYSTEM REQUIREMENT:

- ✧ Microsoft Windows 8.1, 8, 7, XP (32-bit or 64-bit)
- ✧ Windows Server 2012, 2008 R2, 2003(32-bit or 64-bit)
- ✧ Mac OS X 10.9 / 10.8 / 10.7 / 10.6
- ✧ Linux Kernel 2.6.14 - 3.5.0
- ✧ Available USB port (USB 3.0 is recommended)

SPECIFICATIONS:

Interface	
Host Interface	USB 3.0 Male Type-A connector
Ethernet Port	RJ-45 Female connector (Gigabit Ethernet)
USB Port	USB 3.0 Female connector
LED	Activity and Link LED indicators
Power	
Power Mode	Bus-powered or Self-powered ***If you are using a high-power USB device please attach the power adapter that came with it or purchase a JUH470 power cord to ensure maximum performance.
Functions	
Display	Video Playback: 1080P Display resolution: 2048 x 1152 @ 32bit Display Modes: Primary, Extended, Mirror Display Rotation: 0°, 90°, 180°, 270°

Ethernet	<p>Transfer Rate: 1000 Mbps (Half Duplex) / 1000 Mbps (Full Duplex)</p> <p>IEEE: IEEE 802.3az, IEEE 802.3, 802.3u, and 802.3ab, IEEE 802.3x</p> <p>Modes:</p> <ul style="list-style-type: none"> - Supports Wake on LAN function, suspend mode and remote wakeup via link-change, magic packet, or Microsoft wakeup frame - Supports IEEE 802.1Q VLAN tagging and 2 VLAN ID filtering - Supports Jumbo Frame - Supports Checksum Offload (IPv4, IPv6, TCP, UDP) and TCP Large Send Offload
Physical Specifications	
Dimensions	<p>Main body: 43.75(W)x 90.6(H)x18.6(D) mm</p> <p>Cable length: 14.5 cm</p>
Weight	Approximately 58.5 g (including cable)

Package Contents

USB 3.0 Multi-Adapter JUH470
 Quick Installation Guide
 Driver CD

REGULATORY COMPLIANCE

FCC

This equipment has been tested and found to comply with FCC Part 15 Subpart B § 15.109/15.107 Class B.

Operation is subject to the following two conditions:

- This device may not cause harmful interference
- This device must accept any interference, including interference that may cause undesired operation of the device.

CE

This equipment is in compliance with the requirements of the following regulations:

EN 55022 Class B (2006),

EN 55024 (1998+A1:2001+ A2:2003), (IEC/EN 61000-4-2 (1995+A1:1998+A2:2001)/-3(2006)

C-Tick

This equipment is in compliance with the requirements of the following regulations:

EN 55022 (2006) Class B, AS/NZS CISPR22 © IEC: 2005.

VCCI

This equipment is in compliance with the requirements of the following regulations:

CISPR22 © IEC: 2005

Disclaimer

Information in this document is subject to change without notice. The manufacturer does not make any representations or warranties (implied or otherwise) regarding the accuracy and completeness of this document and shall in no event be liable for any loss of profit or any commercial damage, including but not limited to special, incidental, consequential, or other damage. No part of this document may be reproduced or transmitted in any form by any means, electronic or mechanical, including photocopying, recording or information recording and retrieval systems without the expressed written permission of the manufacturer.

WARRANTY OF j5 create

j5 create offers a limited 1-year warranty. User's wear & tear damage is not included.

The user shall call or email **j5 create** customer service with defect information of the product and obtain a return authorization number.

Users are responsible for one way return freight cost and we will take care of one way freight back.

In order to obtain a return authorization, user should have the following information handy when calling or emailing the service team:

- (i) a copy of original purchase invoice to verify your warranty
- (ii) a product serial number
- (iii) a description of the problem
- (iv) a return Material authorization number
- (v) customer's Name, address, and telephone number

j5 create does not warrant that the operation of the product will be uninterrupted or error-free. **j5 create** is not responsible for damage arising from failure to follow instructions relating to the product's use. This warranty does not apply to:(a) consumable parts, unless damage has occurred due to a defect in materials or workmanship; (b) cosmetic damage, including but not limited to scratches, dents ,and broken plastic on ports; (c) damage caused by use with non-**j5 create** products; (d) damage cause by natural disasters (flood, fire, earthquake, lighting strike, typhoon etc..)(e) damage caused by human misuse(lost, accident, abuse, misuse or other external causes) (f) damage caused by operating the product outside the permitted or intended uses described by **j5 create** ; (g) damage caused by service (including upgrades and expansions) performed by anyone who is not a representative of **j5 create** or a **j5 create** Authorized Service Provider; (h) a product or part that has been modified to alter functionality or capability without the written permission of **j5 create**; or (i) if any **j5 create** serial number on the product has been removed or defaced.

If such a situation occurs, **j5 create** will calculate the cost of materials and repair for your reference.

This warranty is given by **j5 create** in lieu of any other warranties express or implied.

Copyright© 2014 **j5 create**. All rights reserved. All trade names are registered trademarks of their respective owners. Features and specifications are subject to change without notice. Product may not be exactly as shown in the diagram

